

Firmware Update Procedure for Customer

This document describes the firmware update process and it should take **approximately 10 minutes of total time to complete**. Please note the current TLM-170V settings. *The update process should not be interrupted* once started as this could result in a non-responsive unit.

1. Requirement

- TLM-170V x 1
- The latest TLM-170V firmware file
- A USB drive
- 12V Power adapter x 1

2. Procedure

1. Please download the latest TLM-170V firmware from the Datavideo Official website www.datavideo.com
2. Please change the file name to mcu.bin, and then please copy the firmware to the USB flash drive.
3. Please power off the TLM-170V (Back of the switch).
4. Please plug the USB drive into the TLM-170V.
5. Please Press and hold the EXIT key and then power on the TLM-170V.
6. The power LED will flash during the software update procedure and the TLM-170V will reboot automatically after the software update is completed.
7. Please check the software version. Please press and hold the EXIT key for 3 seconds and then release it, please press the MENU key for 3 seconds and then release it. Finally, please press the EXIT key for 3 seconds, the OSD will display the software version.

