

## Firmware Update Procedure for Customer

Datavideo usually releases new firmware containing new features or reported bug fixes from time to time. Customers can either download the SE-650 firmware as they wish or contact their local dealer or reseller for assistance.

The firmware upgrade process should take ***approximately 10 minutes to complete***. The existing SE-650 settings should persist through the ***firmware upgrade process, which should not be interrupted once started*** as this could result in a non-responsive unit.

### **Procedure**

1. Please visit [www.datavideo.com](http://www.datavideo.com) and download the latest version of firmware.
2. Please unzip the downloaded firmware "**SE-650 SE-700 USB vx.x.x.x.zip**".
3. You will see "Datavideo" folder, "SE-650 Software Release Note" and "SE-650 FW Update Procedure".
4. Please copy and save the "Datavideo" folder in the root directory of the thumb drive.
5. Connect the thumb drive containing the latest SE-650 firmware to the **F/W UPGRADE** Port.
6. Enter "**MENU**" and select "**SETUP**" option.
7. In the "**SETUP**" option, select "**UPGRADE**" and press the "**ENTER**" button to start the upgrade.
8. When the "**UPGRADE**" sub-option turns to green from red, it indicates that the firmware upgrade is complete.
9. Reboot the SE-650 to complete the firmware upgrade.